

# AMPROBE ACF-3000AK



- For use with multimeters or any instrument with AC milli-volt input
- Measures up to 3000A AC
- Connects directly to an instrument
- Flexible head fits all, small conductors and large bus-bars up to 7" in diameter
- Wide frequency bandwidth
- Low battery indicator
- Rugged design, yet lightweight and flexible
- Accuracy:  $\pm 1\%$  of range

## FEATURES

<b>UPC/DCI:</b>	0 95969 36748 6
<b>Battery Life:</b>	200 Hr typical
<b>Size:</b>	10.00x6.50x2.25 inch
<b>Weight:</b>	1.4 lb
<b>Safety:</b>	BS EN 61010-1: 1993, 600V CAT III Pol. Deg 2

## SPECIFICATIONS

<b>Measuring Ranges:</b>	30A/300A/3000A
<b>Output Sensitivity:</b>	100mV/10mV/1mV/A (AC coupled)
<b>Frequency Range:</b>	10Hz to 20kHz
<b>Power Supply:</b>	2 x AA MN1500 (1.5V) LR6 batteries
<b>Low Battery Indication:</b>	Red LED